

# Sequential Direction Light Set LED

- Consisting of 1 master lamp and up to 9 slave lamps
- Robust cable plug connection between the single lamps
- With solar switch
- Fits all beacon systems when using the appropriate adapter (42 mm Ø, 40 x 40 mm)
- Adjustable as guide light, sequential direction light, flashing light, steady light



<b>Light colour</b> yellow	<b>Eff. light intensity</b> 1500 cd	<b>Av. power consumpt. day</b> 1.3 A	<b>Operating voltage</b> 12/24 V
<b>Blink-/flash rate</b> 60 fl./Min.	<b>Light source</b> 1 LED	<b>Dimensions</b> 207 x 88 x 270 mm (single lamp)	<b>Weight</b> 0.6 kg (single lamp)

## Sequential Direction Light Set LED

### Order number

10-fold Sequential Direction Light Set LED Type 640, 230/12V without beacons 120911-1


## Accessories and Spareparts

### Order number

Charger 230/12V, 17A 220909-2  
 Remote control for Sequential Direction Light Set type 640 329301-01  
 Box for rechargeable batteries 12 V up to 230 Ah, lockable 190230-1  
 Cascade lamp 200 LED, yellow without beacons 122216-01  
 Battery central feed with connector housing 400210-05

## Operating time with a battery pack

With rechargeable battery 12 V, 100 Ah 10-fold system - 80 hrs  
 With rechargeable battery 12 V, 180 Ah 10-fold system - 140 hrs  
 With rechargeable battery 12 V, 230 Ah 10-fold system - 180 hrs



Fixation at a Standard Beacon



Box for rechargeable battery, lockable



Remote control for Sequential Direction Light Set



Battery central feed with connector housing



Further information  
 NIS-01983  
 Entry on [nissen-germany.com](http://nissen-germany.com)

